



**BTR 700 CHANNEL MAP** **A2 Band**

Base Tx	22		23		24	
	518	524	524	530	530	536
Bp Tx	41		42		43	
	632	638	638	644	644	650

Pair Groups = 24 (12a + 12b)																									
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b	
Tx	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	
1	522.3	521.5	528.3	527.5	534.3	533.5	522.6	520.7	528.6	527.7	534.6	533.7	523.3	520.6	529.4	526.4	534.6	533.7	522	522.7	528	528.7	534	534.7	
Rx	41,42,43		41,42,43		41,42,43		41,42		41,42		41,42		42,43		42,43		42,43		41,43		41,43		41,43		
1	632.2	632.2	632.2	632.2	632.2	632.2	632.5	632.5	632.5	632.5	632.5	632.5	638.5	638.5	638.5	638.5	638.5	638.5	632.1	632.1	632.1	632.1	632.1	632.1	632.1
2	632.7	632.7	632.7	632.7	632.7	632.7	632.8	632.8	632.8	632.8	632.8	632.8	638.8	638.8	638.8	638.8	638.8	638.8	632.4	632.4	632.4	632.4	632.4	632.4	632.4
3	634.5	634.5	634.5	634.5	634.5	634.5	633.3	633.3	633.3	633.3	633.3	633.3	640.7	640.7	639.9	639.9	639.3	639.3	632.9	632.9	632.9	632.9	632.9	632.9	632.9
4	637	637	637	637	637	637	635.6	635.6	635.6	635.6	635.6	635.6	642	642	642	642	641.6	641.6	635.2	635.2	635.2	635.2	635.2	635.2	635.2
5	640	640	640	640	640	640	637.6	637.6	637.6	637.6	637.6	637.6	644.3	644.3	644	644	643.6	643.6	636.9	636.9	636.9	636.9	636.9	636.9	636.9
6	643.5	643.5	643.5	643.5	643.5	643.5	640.1	640.1	640.1	640.1	640.1	640.1	646.3	646.3	646.5	646.5	646.1	646.1	637.8	637.8	637.8	637.8	637.8	637.8	637.8
7	644.7	644.7	644.7	644.7	644.7	644.7	641.3	641.3	641.3	641.3	641.3	641.3	648	648	648.8	648.8	647.3	647.3	644.5	644.5	644.5	644.5	644.5	644.5	644.5
8	648.4	648.4	648.4	648.4	648.4	648.4	642.8	642.8	642.8	642.8	642.8	642.8	648.8	648.8	649.6	649.6	648.8	648.8	647.5	647.5	647.5	647.5	647.5	647.5	647.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	22	23	24	22	23	24	22	23	24	22	23	24
1	521.5	527.1	533.7	522.6	528.6	534.6	522.6	528.6	534.6	522.6	528.6	534.6
Rx	41,42,43	41,42,43	41,42,43	41	41	41	42	42	42	43	43	43
1	632.1	632.2	632.3	632.2	632.2	632.2	638.2	638.2	638.2	644.2	644.2	644.2
2	632.5	632.7	632.7	632.7	632.7	632.7	638.7	638.7	638.7	644.7	644.7	644.7
3	634.4	636.3	635	633.4	633.4	633.4	639.4	639.4	639.4	645.4	645.4	645.4
4	637.8	637.5	637.5	636.1	636.1	636.1	642.1	642.1	642.1	648.1	648.1	648.1
5	641.5	641.2	643	---	---	---	---	---	---	---	---	---
6	642.9	644.1	644.7	---	---	---	---	---	---	---	---	---
7	645.9	646.6	647.7	---	---	---	---	---	---	---	---	---
8	647.1	649.6	649.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:**
- 1) Groups 25 - 36 are user-programmable and are blank initially.
  - 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
  - 3) "----" = Blank
  - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



**BTR 700 CHANNEL MAP**      **B4 Band**

Base Tx	25		26		27	
	536	542	542	548	548	554
Bp Tx	47		48		49	
	668	674	674	680	680	686

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27	25	25	26	26	27	27
1	540.3	539.5	546.3	545.5	552.3	551.5	540.6	538.7	546.6	545.7	552.6	551.7	541.3	538.6	547.4	544.4	552.6	551.7	540	540.7	546	546.7	552	552.7
Rx	47,48,49		47,48,49		47,48,49		47,48		47,48		47,48		48,49		48,49		48,49		47,49		47,49		47,49	
1	668.2	668.2	668.2	668.2	668.2	668.2	668.5	668.5	668.5	668.5	668.5	668.5	674.5	674.5	674.5	674.5	674.5	674.5	668.1	668.1	668.1	668.1	668.1	668.1
2	668.7	668.7	668.7	668.7	668.7	668.7	668.8	668.8	668.8	668.8	668.8	668.8	674.8	674.8	674.8	674.8	674.8	674.8	668.4	668.4	668.4	668.4	668.4	668.4
3	670.5	670.5	670.5	670.5	670.5	670.5	669.3	669.3	669.3	669.3	669.3	669.3	676.7	676.7	675.9	675.9	675.3	675.3	668.9	668.9	668.9	668.9	668.9	668.9
4	673	673	673	673	673	673	671.6	671.6	671.6	671.6	671.6	671.6	678	678	678	678	677.6	677.6	671.2	671.2	671.2	671.2	671.2	671.2
5	676	676	676	676	676	676	673.6	673.6	673.6	673.6	673.6	673.6	680.3	680.3	680	680	679.6	679.6	672.9	672.9	672.9	672.9	672.9	672.9
6	679.5	679.5	679.5	679.5	679.5	679.5	676.1	676.1	676.1	676.1	676.1	676.1	682.3	682.3	682.5	682.5	682.1	682.1	673.8	673.8	673.8	673.8	673.8	673.8
7	680.7	680.7	680.7	680.7	680.7	680.7	677.3	677.3	677.3	677.3	677.3	677.3	684	684	684.8	684.8	683.3	683.3	680.5	680.5	680.5	680.5	680.5	680.5
8	684.4	684.4	684.4	684.4	684.4	684.4	678.8	678.8	678.8	678.8	678.8	678.8	684.8	684.8	685.6	685.6	684.8	684.8	683.5	683.5	683.5	683.5	683.5	683.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	25	26	27	25	26	27	25	26	27	25	26	27
1	539.5	545.1	551.7	540.6	546.6	552.6	540.6	546.6	552.6	540.6	546.6	552.6
Rx	47,48,49	47,48,49	47,48,49	47	47	47	48	48	48	49	49	49
1	668.1	668.2	668.3	668.2	668.2	668.2	674.2	674.2	674.2	680.2	680.2	680.2
2	668.5	668.7	668.7	668.7	668.7	668.7	674.7	674.7	674.7	680.7	680.7	680.7
3	670.4	672.3	671	669.4	669.4	669.4	675.4	675.4	675.4	681.4	681.4	681.4
4	673.8	673.5	673.5	672.1	672.1	672.1	678.1	678.1	678.1	684.1	684.1	684.1
5	677.5	677.2	679	---	---	---	---	---	---	---	---	---
6	678.9	680.1	680.7	---	---	---	---	---	---	---	---	---
7	681.9	682.6	683.7	---	---	---	---	---	---	---	---	---
8	683.1	685.6	685.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:**
- 1) Groups 25 - 36 are user-programmable and are blank initially.
  - 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
  - 3) "----" = Blank
  - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



**BTR 700 CHANNEL MAP**      **C3 Band**

Base Tx	28		29		30	
	554	560	560	566	566	572
Bp Tx	44		45		46	
	650	656	656	662	662	668

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30
1	558.3	557.5	564.3	563.5	570.3	569.5	558.6	556.7	564.6	563.7	570.6	569.7	559.3	556.6	565.4	562.4	570.6	569.7	558	558.7	564	564.7	570	570.7
Rx	44, 45, 46		44, 45, 46		44, 45, 46		44, 45		44, 45		44, 45		45, 46		45, 46		45, 46		44, 46		44, 46		44, 46	
1	650.2	650.2	650.2	650.2	650.2	650.2	650.5	650.5	650.5	650.5	650.5	650.5	656.5	656.5	656.5	656.5	656.5	656.5	650.1	650.1	650.1	650.1	650.1	650.1
2	650.7	650.7	650.7	650.7	650.7	650.7	650.8	650.8	650.8	650.8	650.8	650.8	656.8	656.8	656.8	656.8	656.8	656.8	650.4	650.4	650.4	650.4	650.4	650.4
3	652.5	652.5	652.5	652.5	652.5	652.5	651.3	651.3	651.3	651.3	651.3	651.3	658.7	658.7	657.9	657.9	657.3	657.3	650.9	650.9	650.9	650.9	650.9	650.9
4	655	655	655	655	655	655	653.6	653.6	653.6	653.6	653.6	653.6	660	660	660	660	659.6	659.6	653.2	653.2	653.2	653.2	653.2	653.2
5	658	658	658	658	658	658	655.6	655.6	655.6	655.6	655.6	655.6	662.3	662.3	662	662	661.6	661.6	654.9	654.9	654.9	654.9	654.9	654.9
6	661.5	661.5	661.5	661.5	661.5	661.5	658.1	658.1	658.1	658.1	658.1	658.1	664.3	664.3	664.5	664.5	664.1	664.1	655.8	655.8	655.8	655.8	655.8	655.8
7	662.7	662.7	662.7	662.7	662.7	662.7	659.3	659.3	659.3	659.3	659.3	659.3	666	666	666.8	666.8	665.3	665.3	662.5	662.5	662.5	662.5	662.5	662.5
8	666.4	666.4	666.4	666.4	666.4	666.4	660.8	660.8	660.8	660.8	660.8	660.8	666.8	666.8	667.6	667.6	666.8	666.8	665.5	665.5	665.5	665.5	665.5	665.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	28	29	30	28	29	30	28	29	30	28	29	30
1	557.5	563.1	569.7	558.6	564.6	570.6	558.6	564.6	570.6	558.6	564.6	570.6
Rx	44, 45, 46	44, 45, 46	44, 45, 46	44	44	44	45	45	45	46	46	46
1	650.1	650.2	650.3	650.2	650.2	650.2	656.2	656.2	656.2	662.2	662.2	662.2
2	650.5	650.7	650.7	650.7	650.7	650.7	656.7	656.7	656.7	662.7	662.7	662.7
3	652.4	654.3	653	651.4	651.4	651.4	657.4	657.4	657.4	663.4	663.4	663.4
4	655.8	655.5	655.5	654.1	654.1	654.1	660.1	660.1	660.1	666.1	666.1	666.1
5	659.5	659.2	661	---	---	---	---	---	---	---	---	---
6	660.9	662.1	662.7	---	---	---	---	---	---	---	---	---
7	663.9	664.6	665.7	---	---	---	---	---	---	---	---	---
8	665.1	667.6	667.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:**
- 1) Groups 25 - 36 are user-programmable and are blank initially.
  - 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
  - 3) "----" = Blank
  - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.



**BTR 700 CHANNEL MAP**      **C6 Band**

Base Tx	28		29		30	
	554	560	560	566	566	572
Bp Tx	53		54		55	
	704	710	710	716	716	722

**NOTICE:**  
 This wireless microphone system cannot be operated in the United States or its territories, and is intended solely for export and use outside of the United States.

Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30	28	28	29	29	30	30
1	558.3	557.5	564.3	563.5	570.3	569.5	558.6	556.7	564.6	563.7	570.6	569.7	559.3	556.6	565.4	562.4	570.6	569.7	558	558.7	564	564.7	570	570.7
Rx	53,54,55		53,54,55		53,54,55		53,54		53,54		53,54		54,55		54,55		54,55		53,55		53,55		53,55	
1	704.2	704.2	704.2	704.2	704.2	704.2	704.5	704.5	704.5	704.5	704.5	704.5	710.5	710.5	710.5	710.5	710.5	710.5	704.1	704.1	704.1	704.1	704.1	704.1
2	704.7	704.7	704.7	704.7	704.7	704.7	704.8	704.8	704.8	704.8	704.8	704.8	710.8	710.8	710.8	710.8	710.8	710.8	704.4	704.4	704.4	704.4	704.4	704.4
3	706.5	706.5	706.5	706.5	706.5	706.5	705.3	705.3	705.3	705.3	705.3	705.3	712.7	712.7	711.9	711.9	711.3	711.3	704.9	704.9	704.9	704.9	704.9	704.9
4	709	709	709	709	709	709	707.6	707.6	707.6	707.6	707.6	707.6	714	714	714	714	713.6	713.6	707.2	707.2	707.2	707.2	707.2	707.2
5	712	712	712	712	712	712	709.6	709.6	709.6	709.6	709.6	709.6	716.3	716.3	716	716	715.6	715.6	708.9	708.9	708.9	708.9	708.9	708.9
6	715.5	715.5	715.5	715.5	715.5	715.5	712.1	712.1	712.1	712.1	712.1	712.1	718.3	718.3	718.5	718.5	718.1	718.1	709.8	709.8	709.8	709.8	709.8	709.8
7	716.7	716.7	716.7	716.7	716.7	716.7	713.3	713.3	713.3	713.3	713.3	713.3	720	720	720.8	720.8	719.3	719.3	716.5	716.5	716.5	716.5	716.5	716.5
8	720.4	720.4	720.4	720.4	720.4	720.4	714.8	714.8	714.8	714.8	714.8	714.8	720.8	720.8	721.6	721.6	720.8	720.8	719.5	719.5	719.5	719.5	719.5	719.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

Single Groups = 12												
Group	13	14	15	16	17	18	19	20	21	22	23	24
Tx	28	29	30	28	29	30	28	29	30	28	29	30
1	557.5	563.1	569.7	558.6	564.6	570.6	558.6	564.6	570.6	558.6	564.6	570.6
Rx	53,54,55		53,54,55		53	53	53	54	54	54	55	55
1	704.1	704.2	704.3	704.2	704.2	710.2	710.2	710.2	716.2	716.2	716.2	716.2
2	704.5	704.7	704.7	704.7	704.7	710.7	710.7	710.7	716.7	716.7	716.7	716.7
3	706.4	708.3	707	705.4	705.4	705.4	711.4	711.4	711.4	717.4	717.4	717.4
4	709.8	709.5	709.5	708.1	708.1	708.1	714.1	714.1	714.1	720.1	720.1	720.1
5	713.5	713.2	715	---	---	---	---	---	---	---	---	---
6	714.9	716.1	716.7	---	---	---	---	---	---	---	---	---
7	717.9	718.6	719.7	---	---	---	---	---	---	---	---	---
8	719.1	721.6	721.6	---	---	---	---	---	---	---	---	---
9	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---

- NOTES:**
- 1) Groups 25 - 36 are user-programmable and are blank initially.
  - 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
  - 3) "----" = Blank
  - 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.