

MA60BT

Pure Resonance Audio MA60BT 7-Channel 60W Commercial Mixer Amplifier with Bluetooth

DESCRIPTION:

The Pure Resonance Audio MA60BT mixer amplifier with built-in Bluetooth and 70V/100V transformer technology provides a simple to operate and reliable 6-input solution with a built in Bluetooth media player for installation in commercial applications. With an easy-to-use interface, balanced and unbalanced inputs, and 70V, 100V, 8 ohm, or 4 ohm outputs, this versatile and compact mixer-amp is an easy choice for any application.

FEATURES:

- 7-channel powered mixer amplifier
- Volume controls for Mic, Media Player, Bass, Treble and Master
- MP3 Player supports USB, TF, Bluetooth and FM Radio
- 70V, 100V, 4, 8 and 16 Ohms speaker outputs
- 60 Watt power output rating
- Supports 1 balanced XLR input (with phantom power), 2 Mic or line switchable inputs, 2 Stereo RCA inputs, and Telephone input with VOX priority and MOH (Music on Hold)
- DIP switches for Mic/Line, phantom power and microphone priority
- LED indicators for protect signal on Mic, Line and telephone inputs
- Short-circuit, clip, overload and high temp protection
- Remote control with replaceable CR2025 3V lithium battery



PRODUCT SPECIFICATIONS:

Rated Power Output	60W
Speaker Outputs	70V, 100V and 4 Ohms, 8 Ohms or 16 Ohms
Connectors	Mic 1 input by balanced XLR with phantom power Input 2-3 Mic/Line switchable unbalanced 6.3 mm phone jack Line 1-2 inputs by RCA; Line output by RCA
Attenuation	Microphone 1-3, line 1-2 and MP3/FM Radio, bass/treble and master
Input	MIC 1-3: 5-8mV, 600Ω Line, 150-470mV, 10KΩ, unbalanced RCA
Line Out	0.775 (0dBV)
Frequency Response	60Hz - 15kHz (±3dB)
S/N Ratio	Line ≥ 85dB, Mic ≥ 72dB
TDH	Less than 0.5%
Protection	Short-circuit, clip, overload, temp protection
Power Consumption	100W
Power Supply	115V 60Hz & 24V DC
Dimensions (H x W x D)	3.54 x 12.6 x 8.27" (90 x 320 x 210 mm)
Weight	9.039 lbs (4.1 kg)

Specifications may change without notice.