

RZMA120BT

4 Zone 120W Commercial Rack Mount Mixer Amplifier with 4 x 120 Watts 4 Ohm, 70V/100V and Bluetooth

DESCRIPTION:

Powerful and feature-packed, the Pure Resonance Audio RZMA120BT is a 4 zone commercial mixer amplifier equipped with built-in MP3, FM tuner, Bluetooth and recording capability. This multi-zone mixer amplifier has 4 x 120-watt output capability at 4 Ohm, 70 and 100 Volts. Advanced matrix technology allows four zone selectable inputs to be assigned to a zone, or across multiple zones with the push of a button. A monitor channel provides a 1 watt 8-ohm output for a control room monitor speaker. A remote microphone can be connected via Cat5 for zone paging, and a convenient IR remote is available for volume and source control.

FEATURES:

- 4 channel amplifier in a 3U 19" rack mount design
- All source inputs can be matrix assigned to different 4 zones output simultaneously
- The 5 channel inputs & MP3 input are designed with separate bass, treble and volume control
- 3 microphone/line inputs with phantom power and gain control
- 2 AUX inputs by RCA with gain control
- MP3 player with TF and USB inputs has a separate power supplied module
- Built-in tuner audio source
- 1 4 zone remote microphone input via RJ45 port
- 4 channel line inputs and speaker outputs
- Versatile speaker outputs for each four channels: 70V, 100V and 4Ω
- RS232 serial control port for third-party system communication
- Priority input to override other inputs (equal to EMC input)
- Input priority level from high to low:
 - Before contact priority control input: MIC1 TEL Remote MIC MIC2= MIC3 = LINE4 = LINE5 = MP3
 - After contact priority control input: TEL MIC1 Remote MIC MIC2 = MIC3 = LINE4 = LINE5 =MP3
- Built-in monitor with volume control
- Extensive protection of thermal, short-circuit, clip and overload with indicators
- Ground lift switch
- Remote control with replaceable CR2025 3V lithium battery



PRODUCT SPECIFICATIONS:

Rated Power Output	4 Zones x 120W
Speaker Outputs	4Ω, 70V/100V
Monitor Output	1W/8Ω
Input Sensitivity and Impedance	CH1, CH2, CH3: MIC: ± 2.5mV/600 Ω PHANTOM: ± 2.5mV LINE: ~175mV/10K Ω balance input CH5-6: 350mV/10K Ω balance input TEL: 350mV/10K Ω REMOTE MIC: ± 387mV/10K Ω
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 100Hz
S/N Ratio	>65dB
LINE 1-4 Output Level	1V/600 Ω (balance output)
Frequency	80 - 16KHz
MP3	Support MP3 format, max capacity of 32GB
TF File System	Only FAT16, FAT32, the biggest one partition, does not support folder to store
Harmonic Distortion	<1%
Power Consumption	800W
Supply Voltage	~120V 60Hz
Dimensions (H x W x D)	5.2 x 19.06 x 17.32" (132 x 483 x 440 mm)
Weight	41.2 lbs (18.69 kg)
Shipping Weight	55 lbs (24.95 kg)