



99 LING ROAD
 ROCHESTER, NY 14612
 800.733.9473
www.whirlwindusa.com

THS Series Comparison Chart

	THS1M	THS1T	THS2	THS3	THS4	THS5	THSR
Mic On/Off	X	X	X	X	X	X	X
Type of Mic On/Off switch	Momentary Push to mute	Momentary Push to talk	Latching	Latching	Latching	Latching	Latching
Cough Switch (Momentary)			X	X	X	X	X
Talkback Mic to line with level control (-20 to +40 dB)			X	X	X	X	X
Stereo In with stereo volume and Mono in (XLR balanced line level)	X	X					
Stereo In with separate L and R volume controls and Mono in (XLR balanced line level)			X				
Assignable input to L or R on HP pre volume control				X			
Assignable input to L or R on HP post volume control					X		
2 Inputs balanced xlr with volume and pan, mic input volume and pan to HP						X	
Master HP volume (stereo)						X	
RTS input (2 unbalanced on xlr) with L/R assignable switches post volume control							X
Headphone power 30 ohms	200 mW	200 mW	200 mW	200 mW	200 mW	200 mW	123 mW
Mic pass thru with no power	X	X	X	X	X	X	X
Phantom power				X	X	X	X
T Power				X	X	X	X
Wall Power Supply	X	X	X	X	X	X	X
RTS powered							X