



**ACT-58H 5.8 GHz Handheld Transmitter**

The ACT-58H handheld transmitter is built on the backbone of four generations of ACT product design and experience. This transmitter features improved RF circuitry that operates in the ISM 5.8 GHz band which is largely interference free making it easy to set up and reliable to use. The ACT-58H has a rugged housing, premium power consumption characteristics for excellent battery life, a lockable silent on/off switch, extremely low handling noise, improved anti-pop characteristics and unsurpassed off-axis rejection. The MIPRO ACT-58H is innovative, reliable and offers the premium performance needed by today's audio professional.

**ACT-58H Features**

- Extremely rugged, ergonomically designed housing
- ACT™ syncs the transmitter and receiver frequency automatically
- Anti-pop, anti-roll, multi-layer steel grill with low handling noise and superior off-axis rejection
- Up to 20 hours battery life from 2 AA batteries
- 4-stage LED battery status turns red under low battery conditions
- Premium MU80 cardioid condenser capsule
- Silent, lockable on/off switch

**Specifications**

Frequency Range	ISM 5.8 GHz — 5,725~5,850 MHz
Channel Set-Up	MIPRO ACT (Automatic Channel Targeting) IR Sync
RF Output Power	20mW
Modulation	Digital
Gain Setting	0 dB = microphone capsule sensitivity
Microphone Capsules	MU80 Cardioid Condenser with switchable 6 dB pad
Battery	AA Alkaline Batteries × 2
Battery Life	Up to 20 hours
Dimensions	2.0" Φ x 9.8"
Weight	8.3 oz. (excluding batteries)

ISO 9001