









MegaVox Pro Public Address System

- Reaches a Distance of 100 Yards
- Lightweight Only 15lbs
- Powerful Horn Amplifier
- Optimal for Voice Amplification
- Up to Two Optional Built-in **Wireless Receivers**
- Comes with Standard Built-in Bluetooth
- Built-in Rechargeable Battery
- Signal Alert Button









MegaVox PRO PA System

Technical Specifications




SIX YEAR WARRANTY

Thousands report the MegaVox PRO as the most reliable Public Address system on the market. Emergency responders like its signal alert siren, wired microphone and convenient shoulder strap. Coaches, band directors and auctioneers appreciate the Bluetooth capability, flexibility of the AC/DC operation and the range of the wireless microphones.

With the MegaVox Pro you're ready for any situation . . . it's lightweight, loud & easy to carry. Just grab it and go!





(MEGA-8000U2 Back Panel Shown)

MEGAVOX MODELS

MegaVox with Bluetooth

MegaVox with Bluetooth

MegaVox with Bluetooth

Unpowered companion speaker

MEGA-8000

MEGA-8000U1

MEGA-8000U2

MEGA-8001

Features

True AC/DC, 110/220V power supply

Reaches a distance of 100 yards

Lightweight - Only 15 lbs

High-efficiency re-entrant horn driver

Powerful horn amplifier

Up to two built-in 16-channel UHF wireless receivers

Comes with standard built-in Bluetooth

Built-in rechargeable battery runs up to 10 hours on a charge

Microphone with coil cord

Signal alert button

External speaker output

External output powers optional MegaVox Pro companion speaker

Durable injection-molded case is tough, fade resistant & UV treated

Speaker stand receptacle molded into case bottom

UHF WIRELESS

WH-8000 Wireless handheld microphone/ transmitter (540-570 MHz)

WB-8000 Wireless body-pack transmitter


(540-570 MHz) (requires handsfree microphone) Microphone options

include:

Over-the-Ear/EM-TA4F, Lapel/LM-60,

Collar/CM-60, Headband/HBM-TA4F

MEGAVOX PRO DAISY-CHAIN & 1 built-in wireless receiver DAISY-CHAIN READY • CONNECT MULTIPLE SYSTEMS & 2 built-in wireless receivers



SIMPLE LINE-OUT TO LINE-IN CONNECTION **EXPANDS YOUR COVERAGE**

TECHNICAL SPECIFICATIONS

Rated Power Output 20 watts Max SPL @ Rated Power 119 dB @ 1 meter Frequency Response 400 Hz - 10 kHz 19V DC/universal input Charger (RC-6000)

(100Vac - 240Vac, 50 - 63Hz)12 volt rechargeable, 5 AH 13"x 9" x 14" (33 x 23 x 36 cm)

15lbs / 6.8 Kg Weight

Inputs Line Mic 1

Hi-Z, unbalanced, 1/4"-phone Lo-Z, unbalanced, 1/4"-phone

(used for wireless on MEGA-6000U1) Lo-Z, unbalanced, 1/4"-phone

Mic 2 Outputs

Line (post fader) Speaker Out

Lo-Z, 1/4"-phone 4Ω , unswitched, 1/4''-phone



Dimensions (HWD)

Battery

(Features & Specifications Subject to Change Without Notice)

800.262.4671

www.anchoraudio.com

Anchor Audio, Inc.

Portable Sound Systems • Carlsbad, California